



***Maverick MV6
Battery Pack
Instructional Manual***

Introduction:

Thank you for your choice in purchasing a Core SWX battery pack. The battery is designed to improve and assist you in your mobile powering requirements. This product is at the pinnacle of technological advancements, offering the features and performance of several different products, making it the most advanced battery product in the industry.

Please read this manual to help you understand and capitalize on the features of this battery.

Features:

- Dynamic multi-voltage output via 2x XLR 4p 14v(DC 11-17v), 2x XLR 3p @28v (regulated), 2x 12v ptap outputs, 5v USB output.
- Backlit Battery Display
- Handlebar LED Indicator
- On-Board Microprocessor stores: Name, Serial Number, Voltage, Temperature, Current, Chemistry Type, Charge Cycles, and Date of Manufacturing.
- Temperature, current, and voltage protection.
- Powder-coated cast aluminum casing provides a shock absorbing, water resistant shell to protect the battery pack.

Operation:

Usage

1. Press the power button down to the ON position(depressed):
 - All outputs are available.
 - Button LED indicator lights up in blue.
 - OLED display will illuminate
2. Press the power button to OFF position:
 - Power outputs become unavailable.
 - Button LED indicator stays off.

Charge Operation

1. Charge via internal AC charger
 - Make sure the discharge system is off. Top panel power button should not be illuminated blue and the top panel OLED should be off.
 - Connect an AC mains power source to the AC input on the side of the MV6 system. Turn on the power switch next to the AC mains input. At that time, the switch will illuminate GREEN and the top panel OLED will begin to display remaining charge time.
 - The LED Handle light will illuminate Solid Green when the system is fully charged.

Backlit Battery Display

The MV6 display is a 3 phase battery status display. This allows you to monitor the battery's performance across three key phases: standby, connected, and charging. In the standby phase, the display shows the available charge level based on a current load of 60 watts. When the battery is connected to a device, the display updates in real-time to recalculate the runtime based on the present load current. Finally, when the battery is plugged into the charger, the display provides an estimate of the time until the battery is fully charged.

Handle LED Indication

Discharge	Charge
From 100% to 16% : No LED From 15% to 5% : Blinking Red LED 5% to 0% : Solid Red LED	Charging : RED LED Fully charged : GREEN LED

Over time the display and power gauge's accuracy is dependent upon a full charge and discharge. At least once every 2 months the battery should be fully cycled(discharged and recharged) so the battery can relearn the capacity of the battery.

Powder-Coated Cast Aluminum Casing

The MV6's powder-coated aluminum casing provides shock-absorbing and water resistant protection to its internal components. Its consistent form factor allows for the RNGXL to be compatible with legacy shipping cases, allowing for maximum versatility.

This compact casing safeguards protects its internals from the world of cinema production. For gentle cleaning, use a soft, lint-free microfiber cloth to gently wipe the surface of the powder-coated aluminum casing. Avoid abrasive materials or harsh chemicals, as they may cause scratches or damage to the protective layer. In general, the casing protects against impacts and vibrations as well as being weather resistant to accommodate for versatile shooting conditions.

Battery Storage

In the event the battery pack won't be used for an extended period of time, store the battery pack at 40% charged in an environment between 10°C and 35°C. Every two months the battery pack should be fully cycled to reduce the change of self discharge and capacity loss.

Notes on Use

- An increase in temperature is normal during charging and discharging.
 - Make sure to keep battery contacts clean.
 - Do not attempt to disassemble the battery. Please contact Core SWX for any service issues. ●
- Keep batteries separated when transporting.
- Keep battery pack dry and avoid use in humid environments.

Specification Data:

Cell Chemistry: Li-Ion

Capacity: 605Wh(14.4v, 42.0Ah, max rating 639wh)

Size: 9.56" x 13.7" x 5.3"

Weight: 28.3 lbs.

Voltage Outputs: 2x XLR 4p 14v(DC 11-17v), 2x XLR 3p @28v (regulated),

Max Load: 20A @ per 14v, 20A @ 28v

Built-in Protections: Temperature(internal), Voltage(internal), Current(resettable external and internal)

Warranty:

This product is warranted to the Original Purchaser against all defects in material and or workmanship for the period herein.

The warranty period shall be 3 years for parts and labor, unless otherwise noted. Core SWX agrees to pay equal return freight costs to return the product the same method it was received. In the event of an issue, the purchaser agrees to the below RMA procedure.

Procedure:

1. Go to <http://www.coreswx.com> and to the the support section to fill out the online RMA form. 2. Print the ~~RMA number confirmation~~, and ship the product needing service to Core SWX, LLC. along with RMA number confirmation, and copy of bill of sale.
3. All shipments must be done either through UPS or FEDEX, and insured if necessary
4. Core SWX, LLC. is not responsible for any lost shipments.

Core SWX reserves the right to repair or replace any defective product under warranty after Core SWX determines which is more practical.

If Core SWX receives defective product for warranty repair and they are found to be defective as a result of misuse or other damage, not caused by normal wear and tear, Core SWX will notify the customer of an estimate of repair. Customer will incur costs. There are no further warranties, either expressed or implied, including warranties of merchantability or fitness for a particular purpose that has any bearing upon this transaction.



91B Commercial St. Plainview NY 11803 USA

Web: www.coreswx.com Email: sales@coreswx.com

Tel: +1 516-595-7488 Fax: +1 516-595-7492

Copyright © 2023

All rights reserved

Disclaimer

The information contained in this manual is believed to be correct at the time of issuance. Core SWX, LLC. reserves the right to make the changes to the information or specifications without obligation to notify any person of such revisions or changes. Changes will be incorporated in new versions of the manual.

Core SWX, LLC. reserves the right to make changes to product design and functionality without notification.

Trademarks

All product trademarks and registered trademarks are the property of Core SWX, LLC. All other trademarks and registered trademarks are the property of the respective companies.